

TABLE OF CONTENTS

Safety instructions	2
General	2
Travel Charger	3
Battery Information	3
Introduction	4
Bluetooth Wireless Technology	4
Mini Bluetooth Headset MD 81436	4
Box Contents	5
Get connected	6
Check the Headset buttons	7
Charging Battery	7
Turning the Headset On or Off	8
Connecting the unit to the mobile phone	9
Pairing the Headset	10
Making and Answering/Ending Calls	11
Trouble Shooting	14
Frequently Asked Questions (FAQ)	15
List of compatible mobile phones	18
Technical Data	20
Conformity	20

SAFETY INSTRUCTIONS



Please read this manual carefully and familiarise yourself with your new Bluetooth Headset before using it for the first time. Please retain this manual for future reference.

General

- Use of unauthorized accessories may result in performance deterioration, injury, product damage, electric shock, and early warranty termination.
- Attempting to disassemble your Headset may damage it and that the warranty will immediately become void.
- Do not leave the Headset in a dusty environment.
- Use only a clean soft cloth to clean your Headset.
- Do not allow children to play with the Headset, as they may injure themselves and damage the Headset.
- Small children playing with the Headset may cause choking if any part is swallowed.
- Do not leave the Headset in a hot or cold environment for long periods of time.
- When the Headset is not in use, always keep it in its case.



Travel Charger



The charger is designed for indoor use ONLY. Do not use it outdoors.

The charger must be connected to the designated power source as marked.

When removing the charger from an outlet, never pull the charger cord, as it may damage the charger.

Battery Information



Note: For first time use, plug the adapter into the Headset and charge it at least 4 hours until the red indicator turns off.

Battery care

Only qualified Service Centres are authorised to remove or replace the Headset battery.

The rechargeable battery has a long service life if treated with care.

The battery can only be charged within the temperature range of -10 °C to 45 °C.

Use the Headset at room temperature for maximum battery life.

The battery life may be reduced if operating in a cold environment.

When the Headset has not been used for a period of two months or more the battery will need fully recharging for 4 hours.

INTRODUCTION

Bluetooth Wireless Technology

Bluetooth is a short- range wireless communication technology. It allows wireless connections between Bluetooth devices such as mobile phones, personal digital assistants (PDAs), desktop and notebooks computers, input-output devices (mouse, keyboards, printers) and other home appliances. Bluetooth refers to a worldwide standard designed to operate in the internationally recognised ISM (Industrial Scientific and Medical) frequency band. Within the ISM band (2.4Ghz - 2.48Ghz) Bluetooth transmissions hop between 79 separate frequencies 1,600 times every second at a communication range of about 10 meters (class II).

Bluetooth Headset MD 81436

The Bluetooth Headset is a Bluetooth device developed using the latest bluetooth technology, which can connect to other bluetooth devices such as mobile phones, desktop or notebook computers, PDAs (with audio gateway profile supported) wirelessly within a range of 10 meters.

BOX CONTENTS

1. Bluetooth headset
2. Travel charger 100/240V
3. Carry bag
4. Necklace and Hook
5. Car Kit Adaptor
6. Earhook
7. Earplug sponges



GET CONNECTED



Check the Headset buttons

- **S1 Button:** Press and hold for 3 seconds to turn on/off the power, Answer calls when hearing ringtone, Volume up (increase Volume) , During power off mode press and hold for 6 seconds to enter the Pairing-mode
- **S2 Button:** press to end calls when finishing communication, press to reject calls, Volume down (decrease Volume)

Charging Battery

The Headset comes with a rechargeable battery included. The battery is not fully charged when it is new. For first time use, it takes 4 hours to fully charge the battery. Normally, it will take about 2 hours to fully charge the battery. With the battery fully charged, the talk time will be 3 to 4.5 hours, and the stand-by time will be about 100 hours.

- Plug the travel charger into a power outlet.
- Connect the power adaptor to the Headset as shown in the picture. Gently press the adaptor until it clicks into place (The red LED on the headset will turn on.)
- When the battery is full, the red LED will turn off.

Turning the Headset On or Off

To turn the Headset on

Press and hold the S1 button for 3 seconds. You will hear two short high pitched tones and the blue LED indicator on the Headset will flash. The Headset is now turned on. Note that when the red LED indicator flashes the Headset battery is low and needs recharging.

To turn the Headset off

Press and hold the S1 button for 3 seconds, then you will hear two short low tone. The Red indicator will flash, and then the Headset will turn off.

CONNECTING THE UNIT TO THE MOBILE PHONE

What is Pairing?

Pairing is a process of associating Bluetooth devices with each other. It will establish a permanent security link between the devices and enable quick access to the services provided without the need to enter passkeys.

Bluetooth Passkey

Each mini headset has a default passkey **1234** for pairing, which is stored in its internal memory. You are usually required to enter the passkey **1234** in a pairing process with a Bluetooth mobile phone or other device, however it depends on the kind of Bluetooth device that the headset is connected to. Please refer to the user's manual of the device for the specific operating instructions.

Paired devices remain paired even when:

- one of the devices is not powered on.
- a service connection is interrupted or the service stopped
- one or both devices are rebooted

Pairing the Headset

You are required to pair the Headset with your mobile phone before using the Headset.

- The Headset must be powered off before initiating the pairing. Hold and keep pressed the S1 button for 6 seconds until the blue and the red LED indicators are flashing alternately. The Headset is now ready for pairing. If you are wearing the Headset during the pairing operation you will hear two short high pitched tones when the Headset is ready for pairing. **Step 1**
- Initiate the Bluetooth pairing process on your mobile phone. This operation varies depending on the maker and model of your mobile phone. Please consult the mobile phone manufacturer's handbook for more specific instructions. **Step 2**
- When your mobile phone asks for a Passkey, enter 1234 and confirm it. (Note: The 1234 is a default pin-code pre-stored in the Headset.) **Step 3**

When pairing is successful, the red indicator will turn off and the blue indicator will flash.

i If the Headset is not in "pairing mode" your mobile phone will not find the Headset. Remember to place your Headset into "pairing mode" before using your phone to detect a Bluetooth device.



If no pairing is possible after a certain period of time (approximately 2 minutes), the Headset will automatically leave "pairing mode" and power off. You will need to repeat steps 1 to 3 again until "pairing" is successful.

Making and Answering/Ending Calls

Once the Headset is successfully paired with your phone, you can use the Headset to make and receive calls. The Headset can be used with voice dialing if your phone supports this feature. For detailed instructions on voice dialing/control, please refer to the handbook of your mobile phone.

Making Calls

1. Using voice dialing

Press the S1 button, wait for a beep and say the name of the person you wish to call.

2. Using the phone keys to make a call

Enter and then dial the number on the mobile phone as you normally do. Once the call has been set up, the sound will be transmitted to your Headset automatically.

3. Redial

Press and hold the S2 button for 3 seconds, to redial the last number you called. The dialled number appears on your mobile phone.

Reject a call

Press and hold the S2 button for 3 seconds to reject an incoming call.

Transfer a call to the mobile phone

Press and hold the S1 button for 2 seconds, to transfer the call to the mobile phone while you are talking on the headset. If you want to transfer the call back to the headset, press the S1 button again.

Answering Calls and Ending Call

When the Headset is powered on, and there is an incoming call, you will hear a musical beep, and also the blue indicator will change to a quick-flashing mode. (When the Headset is in stand-by, the blue indicator will be in a slow-flashing mode.)

Using the headset with VoIP devices

This headset can be used with any Bluetooth enabled Desktop, Laptop or PDA that's with internet connection and supports the Ausio Gateway Profile. You can use your headset then as microphone and speaker of your original VoIP system, such as Skype, MSN Messenger e.t.c..

- When the Headset rings, press the S1 button to answer.
Adjust the Headset volume by pressing the S1 button for volume UP and the S2 button for volume DOWN.

- End calls by holding the S2 button for 3 seconds or just do nothing and wait for the other person to 'hang up'.

When Headset is powered off and you receive an incoming call, press and hold the S1 button for 3 seconds to turn on the Headset and then press the S1 button again to answer the call.

i Due to the many different designs of mobile phones, an auto-disconnect may occur even when the Headset is powered on. In that case, the Headset won't ring when there is an incoming call. Press the S1 button for 1 second to reconnect the Headset with the mobile phone for an incoming call.)

Mute

Press both the S1 and S2 buttons and hold for one second for the Mute function. Press again, both the S1 and S2 buttons and hold for one second, to disable the mute function.

Low Battery

When the red LED starts to flash, it indicates that the Headset is running on low battery.

Charge the Headset for 2 hours until the red LED turns off.

CLEANING AND DISPOSAL

Cleaning

Clean the headset regularly after use.

Wipe the headset with a damp cloth and mild soap solution.

Disposal



Packaging is raw material and can be re-used or added to the recycling system.



At the end of its life, the appliance must not be disposed of in household rubbish. Enquire about the options for environmentally-friendly disposal.

TROUBLE SHOOTING

The red LED indicator flashes.

It indicates that the Headset is running on low battery. Charge the Headset for 2 hours until the red LED indicator turns off.

The Headset cannot be activated of having been charged for 20 minutes.

To activate the Headset , it needs to charge for at least 40 minutes however it is highly recommended that you fully charge the battery for 2 hours (or 4 hours in some circumstances).

No indication of charging is shown.

If the Headset battery is completely empty or the Headset has not been used for a long period of time it may take a couple of minutes for the LED indicator to show charging status with a steady light.

No contact between the Headset and other devices.

Make sure that the two devices have been paired.

Make sure that the Headset is turned on.

Make sure that the two devices are within a working range.

Make sure that your Mobile Phone is turned on and has a strong signal range.

Some Bluetooth mobile phones can support only one Bluetooth Headset.

Disconnection may happen when there is more than one Headset paired with your mobile phone.

FREQUENTLY ASKED QUESTIONS (FAQ)

1. Why doesn't the Headset work with my mobile phone after the Headset has been fully charged and switched on?

A: You have to activate the Bluetooth function of your mobile phone first and then pair it with the Headset.

2. Does the Headset work with all types of mobile phones?

A: No. It works only with Bluetooth enabled mobile phones.

3. What is the operation distance between the Headset and a Bluetooth mobile phone?

A: The Headset has been tested and approved by BQB. It is fully compliant to Bluetooth v. 2.0, class II, Headset Profile. The maximum operation distance can be up to 10 meters, however it will be affected and shortened by different circumstance and different brands of mobile phones. Some mobile phones have a lesser Bluetooth operating range (less than 10 m).

4. When my mobile phone was searching the Headset why did several Bluetooth devices appear on my mobile phone?

A: Most Bluetooth enabled mobile phones with Bluetooth function activated can detect more than one Bluetooth device within the operating range (10 metres). The Headset will appear as "BT Headset" or "Unknown Device" on your mobile phone before it has been fully detected.

5. Why does my mobile phone not find the Headset?

A: If the Headset is not in 'pairing mode', your mobile phone won't find the Headset. Set the Headset to 'pairing mode' be-

fore using your mobile phone to search for the Headset and detect it. Refer to your specific mobile phone's handbook for more detailed instructions.

6. Do I need to pair the Headset with my mobile phone every time I switch on my mobile phone or the Headset?

A: No. Once the Pairing is set up between the two devices, they will remain paired even when one or both devices are powered off.

7. Why does a strange noise or interference static sometimes come from the Headset?

A: The performance of the Headset can be affected by a weak mobile phone signal. Move to an area where your mobile phone has a strong network signal.

8. When I can't hear very well with the Headset what should I do?

A: Adjust the sound volume on your mobile phone, or press and hold the S1 button on the Headset to increase the volume. Also, make sure your mobile phone has a good network signal.

9. Why does the Headset suddenly stop working?

A: The headset may have run out of battery power. When the Headset has a low battery the red LED indicator will flash. Some Bluetooth enabled mobile phones which do not include the correct Bluetooth implementation will occasionally freeze the Bluetooth status and will need to be restarted. If this happens, remove the battery of your mobile phone and then replace it. Turn on your mobile phone. It is not necessary to

'pair' the phone and Headset again.

Always make sure that your Bluetooth phone has the latest version of firmware loaded. Please check the website or email your mobile phone manufacturer for details of the current firmware for your phone model.

10. Why is the voice dialling function not working with the Headset?

A: You may have to record your voice through the Headset so that the mobile phone correctly understands what you are saying.

Nokia phones are not compatible with voice dialling from the Headset.

LIST OF COMBATIBLE MOBILE PHONES

LG

LG Electronics Chocolate

Motorola

Motorola Razr V3i

Motorola RAZR V3x

Motorola SLVR L7

Nokia

Nokia 3250

Nokia 6230i

Nokia 6280

Nokia N70

Nokia N73

Nokia N80

Nokia N91

Nokia N93

Samsung

Samsung SGH-D600

Samsung SGH-D800

Samsung SGH-D820

Siemens

Siemens EF81

Sony

Sony Ericsson V630i

Sony Ericsson K750i

Sony Ericsson K800i

Sony Ericsson W800i

Sony Ericsson W810i

Sony Ericsson W850i

Sony Ericsson W900i

Sony Ericsson W950i

TECHNICAL DATA

Mains operation: AC 100V-240V~50/60Hz

Power output: DC 5.0V

Conformity

Hereby, Medion AG, declares that this type Bluetooth Headset MD 81436 is in compliance with the essential requirements and other relevant provisions of Directive 1999/5/EC.

If you require you may obtain further information on the conformity with the European Directives from our Service Center.

C €0470

Tested to be used in all EU-countries!